

## POWER TRANSFORMER CHASSIS MOUNT: QUICK-CONNECT WORLD SERIES TM

# **VPS36-2200**

### **Electrical Specifications (@25C)**

1. Maximum Power: 80VA

2. Input Voltage: **Series:** 230VAC, 50/60Hz; **Parallel:** 115VAC, 50/60Hz 3. Output Voltage: **Series**<sup>1</sup>: 36.0V CT@ 2.2A; **Parallel**<sup>2</sup>: 18.0V @ 4.4A

4. Voltage Regulation: 25% TYP @ full load to no load 5. Temperature Rise: 30C TYP (45C MAX allowed)

6. Insulation Resistance:  $100M\Omega$ 

7. Recommended Fuse3:

Series: Littelfuse p/n 313 2.5 HXP, 2.5A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BKMDL-2½, 2.5A 250V, ¼ x 1 ¼ Parallel: Littelfuse p/n 313 5.0 HXP, 5A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BKMDL-5, 5A 250V, ¼ x 1 ¼

#### **Construction:**

Dual bobbin construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements.

#### Safety:

These units are designed with 4000VAC isolation between the primary and secondary, and also, between each winding and the core.

#### **Agency File:**

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose. File E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3

CSA: File LR 221330. C22.2 NO. 66, General Purpose.

TUV Certificate No.: R72103639, EN60950, Information Technology







A. Dimens	ions:		Unit: In inches				
Н	W	D	В	С	Т	MW	ML
3	2-1/2	2-5/16	1-3/8	5/16	3/16	2	2-1/4

B. Mounting Hole Size: 13/64 x 3/8"

C. WT Lbs.: 2.8

D. Terminal Size: 0.187" x 0.020"

### Connections4:

Input: Series - 6 and 1, Jumper 5 to 2

Parallel - 6 and 1, Jumper 6 to 2 and 5 to 1

Output: Series - 12 and 7, Jumper 11 to 8

Parallel - 12 and 7, Jumper 12 to 8 and 11 to 7

**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


<sup>2</sup> Non-Inherently limited. Class 2 not wet, Class 3 wet.


<sup>3</sup> Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.


<sup>&</sup>lt;sup>4</sup> Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.











Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

Harley Knox Blvd.
Publish Date: October 13, 2016

<sup>&</sup>lt;sup>1</sup> Non-Inherently limited. Class 3.